



Website: www.wundercurrent.in | +91 9313197730 | wundercurrentev@gmail.com

Wundercurrent W2 Ultra & W3 Ultra - 6 in 1 Digital Energy Meter

Functions:

- **Measures:** Voltage, Current, Power (Active), Energy, Frequency, Power Factor
- **Overload Alarm:** Alerts with flashing backlight and power for exceeding set power threshold.
- **Power Alarm Threshold:** Set your desired power limit for alarm activation.
- **Resettable Energy:** Clear accumulated energy readings with a key press.
- **Data Retention:** Stores data even during power outages.
- **Large LCD Display:** Shows all six parameters simultaneously.
- **Backlight Function:** Improves display visibility (with memory function).



Display & Key Functions:

- **Display:**
 - **Power:** 0 - 22000W (various display formats based on wattage)
 - **Energy:** 0 - 999kWh (various display formats based on kWh)
 - **Voltage:** 80 - 260V
 - **Current:** 0.02A and above (various display formats based on Amps)
 - **Frequency:** 45 - 65Hz
 - **Power Factor:** 0.00 - 1.00PF
- **Key:**
 - **Backlight:** Short press to turn on/off (remembers last state).
 - **Reset Energy:** Long press for 5 seconds (follow additional steps for confirmation).
 - **Set Power Alarm Threshold:** Long press until "SET CLr" appears, then follow steps to adjust and save the desired threshold (0.0 - 22kW).